




PDU Technical Specification

File No. :

Date: 2016-5-17

|                    |                         |                        |  |
|--------------------|-------------------------|------------------------|--|
| <b>Client</b>      | Interlink               | <b>RoHS</b>            | /  |
| <b>Description</b> | Power distribution unit | <b>Client Part No.</b> | /  |
| <b>Part No.</b>    | CH-20920                | <b>Client Code No.</b> | Interlink  |
| <b>Part Code</b>   |                         | <b>Delivery time</b>   | /  |
| <b>Quantity</b>    |                         | <b>Remarks</b>         | 1. Pay attention to the silk-screened direction of Logo on Drawing<br>2. The product is single line 32A input, A line and B line (from top to bottom) 16A output, each line output is with serial port ampere-voltage energy meter |

| NO. | Parameters and Description   |  | NO.  | Parameters and Description              |   |
|-----|--|--|--|---|---|
| 1   | Socket Type and Quantity   | 20 way Universal Outlet                    | 9  | Color of Enclosure                      | Black   |
| 2   | Socket Combination   | /  | 10   | Product Size(L*W*H)                     | 1604x44.4x44.45mm   |
| 3   | Inner Circuit Connection   | 12AWG、14AWG Electronic Wire, Φ2.0mm Copper | 11   | Mounting Length                         | 1580mm  |
| 4   | Input Method for Power Supply  | Cable                                      | 12   | Case Length of Aluminum Alloy           | 1550mm  |
| 5   | Cable Plug   | Industrial Waterproof plug 32A             | 13   | Product Mounting                        | Bracket   |
| 6   | Cable Specification  | 3*6mm <sup>2</sup> *3m                     | 14   | Bracket Install                         | Vertical Frontal  |
| 7   | Cable Mounting Method  | Bottom input                               | 15   | Control Indicating Function Requirement | /   |
| 8   | Cable Fixing   | 8R3  | 16   | Monitoring Function Requirement         | Serial Port Current Voltage Watt-hour Meter , single pole circuit breaker |
| 17  | Module installation order (from left to right or from top to bottom) |  | See below drawing  |   |   |
| 18  | Accessories Required   |  | 2 pcs for Brackets ,M6 Screws; M6 flat washers, M6 spring washers, M6 nuts           |   |   |
| 19  | Logo   | Product Name                               | Power distribution unit  | LOGO Picture                            |   |
|     |  | Model No.                                  | CH-20920   |   |   |
|     |  | Rated Voltage/Current                      | 220V AC 32A  |   |   |
|     |  | Product LOGO                               |  |   |   |

**Drawing**

